

CODE EZY 200 CAP RECEIVER

The Receiver will hold 200 remotes all on one channel or 200 remotes over 2 channels in any combination - for example 100 on Channel 1 100 on Channel 2.

Learning Momentary Mode (use for Garage and Gates)

Option 1: Select Channel 1 by pressing the Learn Button ONCE on the receiver then release.

Option 2: Select Channel 2 by pressing the Learn Button TWICE on the receiver and then release.

Step 1: Once a Channel has been selected the LED stay solid

Step 2: Press the button required on remote control. LED will flash 5 times and turn off.

This indicates learning has been successful.



Deleting Codes

Step 1: Press Delete Button and Hold down until LED light comes on.

All Remotes are now deleted.



Installation Instructions for Code Ezy 200 Capacity
Receiver

www.retroremotes.com.au
0417 223 200